



TBNP dies.

For **overhead line connectors** for alloy Al conductors, hexagonal crimping.

mm ²	Dies	No. of crimps
31-99	TBNP16-20	Die side 16: 2x5 Die side 20: 2x10




TBC dies.

For Cu, branch connectors (C-sleeves), oval crimping.

Dies	Main conductor mm ²	Branch mm ²	Crimp in die nest	No. of crimps
TBC4-C8-9	10-6	10-6	C4*	1
	50-16	50-16	C8-9	2
TBC5-C6	16-10	16-6	C5	1
	25-16	25-16	C6	1

* Die nest marked C4A to be used for 6 mm² main to 6 mm² branch.



One resp. two crimps.



Matrix holder TV2620, matrix TP13M and punch TP13D.

Punch and matrix

For Al terminals and connectors, indent crimping.

Stranded mm ²	Solid mm ²	Matrix holder	Matrix	Punch
16-25	16-35	TV2620	TP13M	TP13D



Always crimp twice on Al.