

APPLICATION

Heat-shrinkable bushing boots are used to increase the creepage distance between the live metal and surrounding metal work and neighbouring phases.



KIT CONTENTS

The RAB/SB kit comprises 3 heat-shrinkable bushing boots and mastic.

6/10 (12) kV
6.35/11 (12) kV
8.7/15 (17.5) kV

Up to 17.5 kV

CLEARANCES

This is an unscreened boot and therefore not safe to touch when energised.

Bushing boot type	Voltage Um (kV)	Description	Conductor sizes (mm ²)	
			min.	max.
RAB 1	17.5 max.	right angle	16	95
RAB 2	17.5 max.	right angle	120	300
RABS1	17.5 max.	right angle short	16	95
RABS2	17.5 max.	right angle short	120	300
SB 1	17.5 max.	straight	16	95
SB 2	17.5 max.	straight	120	300